

# Linux

## Preparations

- Installation of the packages
  - python3-smbc
  - smbclient / samba-client
  - system-config-printer
- configuration of the file /etc/samba/smb.conf
  - workgroup = HS-WOE
- reboot the device

## Multifunction Devices

**Driver:** First you need to download and unzip a printer driver for the multifunction devices.

- Go to the [Utax driver website](#)
- Select the following driver
  - Product group: Copier systems
  - Product name: 3005ci
  - Operating system: Linux
- Download this driver and unzip it locally on your hard drive.

**Device:** System Preferences / Printers

- Add / Network Printer / Windows Printer via SAMBA
  - SMB printer: smb://ccm-qpilot-1.hs-woe.de/QPilot
  - Legitimization
    - User name: [default login](#) (form: ma1150)
    - Password: <your password>
  - Driver: Provide PPD file
    - Go to the location of the unpacked driver files and select.
      - 3005ci series / 64bit / EU / German / TA5555ci.PPD
    - Installable options
      - Paper feeders: Cassettes (3,4)
  - Printer name: QPilot
  - Description: Multifunction devices
  - Location: Campus Jade HS

From:  
<https://hrz-wiki.jade-hs.de/> - **HRZ-Wiki**

Permanent link:  
<https://hrz-wiki.jade-hs.de/en/tp/mfd/linux>

Last update: **2020/12/11 14:02**



